

Memory Requirements for the Cisco ASA Adaptive Security Appliances Software Version 8.3 and Later

As additional software feature enhancements are introduced on the Cisco[®] ASA 5500 Series Adaptive Security Appliances, the minimum memory requirements are changing for the Cisco ASA 5505, ASA 5510, ASA 5520, and ASA 5540 models. These requirements are for software releases starting with the Cisco ASA Software Version 8.3. Cisco ASA appliances running Cisco ASA 8.3 that do not meet the minimum memory requirement are not supported. Table 1 outlines the new and existing RAM requirements. Note that the memory requirements for the Cisco ASA 5550 and ASA 5580 have not changed.

Table 1. Overview of New and Existing RAM Requirements

Cisco ASA Model	Minimum RAM Requirements (pre Cisco ASA 8.3)	Minimum RAM Requirements (post Cisco ASA 8.3)	Default Shipping RAM on New Cisco ASA Adaptive Security Appliances (as of Feb. 2010)
5505 10-User	256 MB	256 MB	512 MB
5505 50-User	256 MB	256 MB	512 MB
5505 Unlimited-User	256 MB	512 MB	512 MB
5505 Security Plus	256 MB	512 MB	512 MB
5510	256 MB	1 GB	1 GB
5510 Security Plus	256 MB	1 GB	1 GB
5520	512 MB	2 GB	2 GB
5540	1 GB	2 GB	2 GB
5550	4 GB	4 GB	4 GB
5580-20	8 GB	8 GB	8 GB
5580-40	12 GB	12 GB	12 GB

ASA Failover Configuration

Both devices in an ASA failover configuration (active-active and active-standby) must have the same RAM memory. Mixed-RAM devices in ASA failover configurations are not supported.

Upgraded Default RAM in Shipping Cisco ASA 5500 Series Adaptive Security Appliances

All Cisco ASA 5505, ASA 5510, ASA 5520, and ASA 5540 appliances will ship with additional default memory to meet the memory requirements for Cisco ASA Software Version 8.3 in February 2010.

Upgrade Paths for Existing Cisco ASA Appliances

Table 2 lists the memory upgrade kits that will enable customers wishing to deploy the Cisco ASA Software Version 8.3 to upgrade their existing Cisco ASA Adaptive Security Appliances.

Table 2. Memory Upgrade Kits for Cisco ASA 5505, ASA 5510, ASA 5520, and ASA 5540

Memory Part Numbers	Product Description
ASA5505-MEM-512=	512 MB Memory for Cisco ASA 5505
ASA5510-MEM-1GB=	1GB Memory for Cisco ASA 5510
ASA5520-MEM-2GB=	2GB Memory for Cisco ASA 5520
ASA5540-MEM-2GB=	2GB Memory for Cisco ASA 5540

Upgrade Paths for Customers with 512-MB Upgrade Kit for Cisco ASA 5510

Customers who have purchased the 512-MB upgrade kit for the Cisco ASA 5510 (ASA5510-MEM-512=) must upgrade to the 1-GB memory upgrade kit (ASA5510-MEM-1GB=) to run the Cisco ASA Software Version 8.3.

For More Information

For more information about the Cisco ASA 5500 Adaptive Security Appliances or the Cisco ASA Software Version 8.3, visit <http://www.cisco.com/go/asa> or contact your local Cisco account representative.



Americas Headquarters
Cisco Systems, Inc.
San Jose, CA

Asia Pacific Headquarters
Cisco Systems (USA) Pte. Ltd.
Singapore

Europe Headquarters
Cisco Systems International BV
Amsterdam, The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.

CCDE, CCENT, CCSI, Cisco Eos, Cisco Explorer, Cisco HealthPresence, Cisco IronPort, the Cisco logo, Cisco Nurse Connect, Cisco Pulse, Cisco SensorBase, Cisco StackPower, Cisco StadiumVision, Cisco TelePresence, Cisco TrustSec, Cisco Unified Computing System, Cisco WebEx, DCE, Flip Channels, Flip for Good, Flip Mino, Flipshare (Design), Flip Ultra, Flip Video, Flip Video (Design), Instant Broadband, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn, Cisco Capital, Cisco Capital (Design), Cisco:Financed (Stylized), Cisco Store, Flip Gift Card, and One Million Acts of Green are service marks; and Access Registrar, Aironet, AllTouch, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Lumin, Cisco Nexus, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, Continuum, EtherFast, EtherSwitch, Event Center, Explorer, Follow Me Browsing, GainMaker, iLYNX, IOS, iPhone, IronPort, the IronPort logo, Laser Link, LightStream, Linksys, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, PCNow, PIX, PowerKEY, PowerPanels, PowerTV, PowerTV (Design), PowerVu, Prisma, ProConnect, ROSA, SenderBase, SMARTnet, Spectrum Expert, StackWise, WebEx, and the WebEx logo are registered trademarks of Cisco and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1002R)