

600W 230V AVR Line Conditioner, Power Conditioner, AC Surge Protector, 3 Outlets

MODEL NUMBER: LR604



Description

600 watt Automatic Voltage Regulation (AVR) system/Protects sensitive electronics, computer accessories and home theater equipment from power-related damage and performance problems/Extends the useful life of connected equipment by providing optimum voltage conditions for enhanced efficiency and cooler internal operating temperatures/Reliable transformer-based voltage correction circuits maintain 230V nominal output during voltage fluctuations between 189 and 247V/Two levels of voltage stabilization offer targeted response for overvoltages and brownouts/Prevents equipment damage and power related performance problems for computer accessories, printers, home theater equipment, a/v components and other sensitive electronic devices/AC surge and EMI/RFI noise suppression/Supports loads up to 600 watts/3 AC outlets/3 diagnostic LEDs display boost, trim and normal operation

Features

- Maintains usable 230V nominal output by boosting undervoltages by 13.4%, starting at 189V and reducing overvoltages by 10.6% starting at 247V
- Protects sensitive electronics, computer accessories and home theater equipment from power-related damage and performance problems
- Extends the useful life of connected equipment by providing optimum voltage conditions for enhanced efficiency and cooler internal operating temperatures
- Two levels of voltage stabilization offers response to overvoltages and brownouts
- Input voltages over 247V are reduced by 10.6%
- Input voltages below 189V are boosted by 13.4%
- 600 watts power handling capability
- 340 joules AC surge suppression
- EMI/RFI noise filtering prevents equipment interaction, system interference, lockups and other power-related audio and video artifacts
- 3 diagnostic LEDs indicate boost, trim and normal AVR operation
- 3 protected IEC-320 C13 outlets
- IEC-320 C14 inlet accepts a variety of country specific cordsets

Highlights

- Automatic voltage regulation (AVR) and AC surge suppression
- Maintains regulated 230V nominal output over an input range of 189 to 247V
- 600 watt / 2.6 amp capacity
- 3 IEC-320 C13 outlets with C14 inlet connection
- LEDs display boost, trim and normal operation

Applications

- Maintains usable output voltage during severe brownouts and overvoltages for printers, fax machines, computers, audio/video equipment, workstations, network nodes, file servers, phone systems, point-of-sale terminals, and other applications requiring steady input power.

Package Includes

- LR604 Line Conditioner
- Warranty information
- Instruction manual



Specifications

| General Info | |
|-------------------------------------|---|
| RoHS | Y |
| OUTPUT | |
| Nominal Output Voltage(s) Supported | 230V |
| Output Receptacles | (3) C13 |
| Output (VA) | 600 |
| Output (Watts) | 600 |
| INPUT | |
| Input Cord Length (ft.) | 6 |
| Input Cord Length (m) | 1.83 |
| USER INTERFACE, ALERTS & CONTROLS | |
| Front Panel LEDs | 3 LEDs show AVR boost, trim and normal status |
| SURGE / NOISE SUPPRESSION | |
| UPS AC Suppression Joule Rating | 340 joules |
| EMI / RFI AC Noise Suppression | 20 dB |
| PHYSICAL | |
| Shipping Weight (lbs.) | 4.8 |
| Shipping Weight (kg) | 2.2 |
| Unit Dimensions (hwd / in.) | 5.25 x 5.5 x 4.8 |
| Unit Dimensions (hwd / cm) | 13.3 x 14 x 12.2 |
| Material of Construction | ABS |
| Receptacle Color | BLACK |
| Form Factors Supported | Small tower |
| CERTIFICATIONS | |
| Certifications | CE Rated |
| WARRANTY | |



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

| | |
|---|-------------------------|
| Product Warranty Period (International) | 2-year limited warranty |
| Product Warranty Period (Mexico) | 2-year limited warranty |
| Product Warranty Period (Puerto Rico) | 2-year limited warranty |

© 2015 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.