

## 4-Port USB-C Hub - USB-C to 4x USB-A - USB 3.0 Hub - Includes Power Adapter

Product ID: HB30C4AFS



This compact USB 3.0 hub expands your connectivity by adding four USB Type-A ports through a single USB Type-C™ or Thunderbolt™ 3 port. It includes a 20-watt power adapter, so you have the versatility to connect power-hungry USB devices, and you can fast-charge your mobile devices using the USB charge-and-sync ports.

### Keep using your current peripherals and devices

By converting your computer's USB-C port into four USB-A ports, you can continue to use all of your existing USB 3.0 devices such as flash drives, external hard drives, and printers (USB 3.0 is also known as USB 3.1 Gen 1). Now you can save money and time by avoiding the added cost and hassle of purchasing new USB-C equipped peripherals.

## **Add USB ports, virtually anywhere you go**

With its compact and lightweight casing, this USB hub is designed for mobility. You can easily tuck it into your laptop bag when traveling, which makes it easy to expand your connectivity almost anywhere you need to.

The 4-port hub takes up minimal desk space when connected in your work area, with a small-footprint design.

## **Charge-and-sync your mobile devices**

With four charge-and-sync ports, this hub helps ensure that your mobile devices are charged and ready to use when you need them. The self-powered hub features USB ports that deliver more power than traditional USB ports, so you can charge your devices faster. The charge provided depends on the number of devices connected and the amount of electrical current each device draws.

## **Designed for versatility**

This self-powered USB 3.0 hub comes with an external power adapter to support power-hungry USB devices. This means you can reliably connect and use larger external hard drives and enclosures.

## **Add four USB 3.0 ports in seconds**

This four-port USB hub is multi-platform compatible, which means it will work with a wide range of laptops. It also works with a range of operating systems such as Windows®, Mac, Linux® and Chrome OS™. It installs automatically once you connect it to your laptop, so you can be up and running in seconds.

The HB30C4AFS is backed by a StarTech.com 2-year warranty and free lifetime technical support.

### Certifications, Reports and Compatibility



### Applications

- Turn your computer's USB-C port into four USB 3.0 Type-A ports
- Perfect for home, office, hot-desk, BYOD (Bring Your Own Device), and CYOD (Choose Your Own Device) environments
- Ideal for desktop, laptop, Ultrabook™, Chromebook Pixel™, and MacBook Pro users who don't have enough USB 3.0 ports available
- Carry the hub with you while you're traveling, and connect your USB devices wherever you go

### Features

- Easily add four USB-A ports to your computer through a USB-C port
- A small-footprint design that's lightweight and compact, for maximum portability
- Fast-charge your mobile devices, with charge-and-sync ports that support USB Battery Charging Specification 1.2
- Built-in USB Type-C cable for less clutter
- Universal, multi-platform compatible, with fast and easy installation, and native support in most operating systems (Windows, Mac, Chrome OS, Linux)
- Plug-and-play, and supports hot-swapping or hot-plugging
- Integrated cable features a small and reversible USB-C connector, and it's Thunderbolt 3 data port compatible
- Backward compatible, for use with your older USB 3.0 and 2.0 devices
- Dongle-style USB hub provides three SuperSpeed USB 3.0 (USB 3.1 Gen 1) ports, with throughput support up to 5Gbps

<b>Hardware</b>	Warranty	2 Years
	Chipset ID	Genesys Logic - GL3523
	Fast-Charge Port(s)	Yes
	Industry Standards	USB 3.0 - Backward compatible with USB 2.0 and 1.1
	Interface	USB 3.0
	Ports	4
	USB-C Device Port(s)	No
	USB-C Host Connection	Yes
<b>Performance</b>	Maximum Data Transfer Rate	5 Gbps
	Type and Rate	USB 3.0 - 5 Gbit/s
<b>Connector(s)</b>	Connector Type(s)	1 - USB Type-C (24 pin) USB 3.0 Male 4 - USB 3.0 A (Fast-Charge, 9 pin, SuperSpeed) Female
	OS Compatibility	OS Independent; No additional drivers or software required
<b>Special Notes / Requirements</b>	<b>Note</b>	USB 3.0 is also known as USB 3.1 Gen 1; this connectivity standard offers speeds up to 5Gbps.  When USB-charged devices are connected to the hub, the provided charge output depends on the number of devices connected, and the amount of power each device draws.
	System and Cable Requirements	Available USB Type-C port - USB 3.0 (5Gbps)
<b>Indicators</b>	LED Indicators	1 - Power (Blue)
<b>Power</b>	Center Tip Polarity	Positive
	Input Current	1 A
	Input Voltage	100 ~ 240 AC
	Output Current	4 A
	Output Voltage	5 DC
	Plug Type	B
	Power Consumption (In Watts)	20
	Power Source	AC Adapter Included
<b>Environmental</b>	Humidity	0~90% RH (Non-condensing)
	Operating Temperature	0°C to 60°C (32°F to 140°F)
	Storage Temperature	-20°C to 60°C (-4°F to 140°F)
<b>Physical Characteristics</b>	Cable Length	4.5 in [114 mm]

	Color	Black
	Enclosure Type	Plastic
	Form Factor	Compact
	Product Height	0.5 in [13 mm]
	Product Length	3 in [75 mm]
	Product Weight	1.4 oz [40 g]
	Product Width	1.6 in [40 mm]
<b>Packaging Information</b>	Shipping (Package) Weight	13.8 oz [390 g]
<b>What's in the Box</b>	Included in Package	1 - 4-port USB 3.0 hub 1 - universal power adapter (NA/JP, UK, EU, AU)

Product appearance and specifications are subject to change without notice.